

WILLIAMS ATTACKBUCKER



Note the tilt of the pickup: The screw pole is under the Low E string, while the slug pole is under the high E string. Attach the pickup to the guitar body with Phillips-head pickup ring screws or equivalent.

Use a nickel five cent coin to gauge the distance between the E strings and the pickup. The coin should just slide between the pickup and the strings.

Use a single 500K pot for this pickup. See the wiring diagram to the right.

You may also use coax cable between the pot and the output jack.

Keep the cable runs as short as possible to help reduce hum.

